

Please follow the instruction closely.

1. Extracted the attached "MH430.zip" to folder you should see two files:  
811P\_8574\_BC.bin  
VL811\_Usb3HubFWUpgradeSetup\_V1.0.exe
2. Run USB3 Hub FW Upgrade Tool (VL811\_Usb3HubFWUpgradeSetup\_V1.0.exe) to start the installation process.
3. Follow the instructions on screen to finish the installation.  
After installing you will see the USB3 Hub FW Upgrade Tool folder listing Bin and Driver folders
4. Delete the "811P\_8554\_BC\_Apple2A.bin" firmware file under the bin folder, then copy the included "811P\_8574\_BC.bin" firmware file in step#1 to the bin folder.
5. Plug the USB 3.0 Hub to the computer's USB 3.0 port and then start "USB3 Hub FW Upgrade" tool.
6. Click the "Start Upgrade" to begin upgrading.
7. Once the upgrade process is finished, USB3 Hub FW Upgrade Tool will display "Upgrade successful". Then power cycle the USB 3.0 Hub to begin using the new firmware.